



DALI DIMMABLE 100 WATT DRIVER

Dimming Function Dali Interface
Output 24 volts DC 100 watts
Dimming Range 0.1% to 100%
Rated 4.16 amps Range 100 - 265 volt AC
Built in active PFC function Efficiency 87%
Protection -short circuit ,over current ,overload ,over temperature
IP66 Protection
Length 230mm
Width 70mm
Height 46mm
3 year warranty
Supplier T-Lighting
Cat Number TLDD100DRV24