



### **DALI DIMMABLE 200 WATT DRIVER**

Dimming Function Dali Interface  
Output 24 volts DC 200 watts  
Dimming Range 0.1% to 100%  
Rated 8.33 amps Range 100 - 265 volt AC  
Built in active PFC function Efficiency 87%  
Protection -short circuit ,over current ,overload ,over temperature  
IP66 Protection  
Length 255mm  
Width 80mm  
Height 53mm  
3 year warranty  
Supplier T-Lighting  
Cat Number TLDD200DRV24