



DALI DIMMABLE 360 WATT DRIVER

Dimming Function Dali Interface

Output 24 volts DC 360 watts

Dimming Range 0.1% to 100%

Rated 15 amps Range 100 - 265 volt AC

Built in active PFC function Efficiency 87%

Protection -short circuit ,over current ,overload ,over temperature

IP66 Protection

Length 280mm

Width 77mm

Height 46mm

3 year warranty

Supplier T-Lighting

Cat Number TLDD360DRV24