



DALI DIMMABLE 50 WATT DRIVER

Dimming Function Dali Interface

Output 12 volts DC 50 watts

Dimming Range 0.1% to 100%

Rated 4.16 amps Range 100 - 265 volt AC

Built in active PFC function Efficiency 98%

Protection -short circuit ,over current ,overload ,over temperature

Safety standards EN61347-1 EN61347-2-13

IP20 Protection

Length 178mm

Width 61mm

Height 24mm

3 year warranty

Supplier T-Lighting

Cat Number TLDD50DRV12